How to use RAA

- ---Beijing Eastforce Superconducting Technology Co., Ltd.
- ---www.eastfs.com




The RAA code has more than 1000 lines, written in ANSYS-APDL language. Before using the RAA code, make sure you have ANSYS with Multiphysics or Emag license on your computer. In general, the RAA is independent to the version of ANSYS. But we recommend ANSYS 14.5 and ANSYS 15.0. as the first choice.

Step 1-1

RUN "Mechanical APDL Product Launcher to set license and Working Directory


Step 1-2

Choose license to Multiphysics or Emag




Step 2 Unzip all the ".mac" files into ANSYS working directory.

File description: 1. RAA_YBCO_step.mac ------- Parameter setting File 2. RAA_YBCO_main.mac------ Geometric Modeling 3. RAA_YBCO_loop.mac--------- Model iteration 4. RAA_YBCO_cal_up.mac------ Loss Calculation 5. RAA_YBCO_output_up.mac----- Result Output Set working directory




The ".mac" file can be edited by any text editing software. We suggest UltraEdit as an editing tool.



The program will run from file 1 to file 5. For the beginners who do not know so much about ANSYS, do **NOT** change any word from file 2 to 5. All you need to do is editing file 1 in which user can change the tape parameters and coil parameters. After editing the "RAA_YBCO_step.mac", save the file.

We recommend using default values without changing any parameters for the first run.

Step 4 RUN the ANSYS program; TYPE "RAA_YBCO_step" into the textbox and ENTER




When the calculation is finished, open the RAA_YBCO_result.txt file in ANSYS working folder to get the results.

- ☐ The fist column indicates the number of the coil.
- ☐ The second column indicates the number of turn in each coil.
- The third column indicates the excitation current.
- ☐ The fourth column indicates the AC loss in each turn.

The AC loss of the magnet only takes account the winding in the first quadrant. To get the total loss including the mirror parts, you should multiply the factor of 2. (Please go to Step 6 to understand the mirror parts)

1	Total time used: 0.44944 Hour			
				0.907E-02 J/cycle
3		ss or the	magnet is	0.907E-02 0/CYCIE
		turn No	Current	Togg (T/guala/m)
	_	_		Loss (J/cycle/m)
	1	1	60.00	0.139E-02
	1	2	60.00	0.110E-02
	1	3	60.00	0.899E-03
	1	4	60.00	0.728E-03
9	1	5	60.00	0.688E-03
10	1	6	60.00	0.713E-03
11	1	7	60.00	0.736E-03
12	1	8	60.00	0.110E-02
13	1	9	60.00	0.112E-02
14	1	10	60.00	0.137E-02
15	2	1	60.00	0.476E-02
16	2	2	60.00	0.375E-02
17	2	3	60.00	0.329E-02
18	2	4	60.00	0.291E-02
19	2	5	60.00	0.269E-02
20	2	6	60.00	0.263E-02
21	2	7	60.00	0.263E-02
22	2	8	60.00	0.274E-02
23	2	9	60.00	0.321E-02
24	2	10	60.00	0.360E-02
25	2	11	60.00	0.442E-02
26				

Take a close look of current distribution and field distribution on winding



Enjoy simulation Enjoy RAA